

NATIONAL BUREAU OF STANDARDS REPORT

8022

MARKOV CHAIN ANALYSIS OF A SORTING MACHINE

by

Joel Levy

Technical Report

to

U.S. Post Office Department



U. S. DEPARTMENT OF COMMERCE
NATIONAL BUREAU OF STANDARDS

THE NATIONAL BUREAU OF STANDARDS

Functions and Activities

The functions of the National Bureau of Standards are set forth in the Act of Congress, March 3, 1901, as amended by Congress in Public Law 619, 1950. These include the development and maintenance of the national standards of measurement and the provision of means and methods for making measurements consistent with these standards; the determination of physical constants and properties of materials; the development of methods and instruments for testing materials, devices, and structures; advisory services to government agencies on scientific and technical problems; invention and development of devices to serve special needs of the Government; and the development of standard practices, codes, and specifications. The work includes basic and applied research, development, engineering, instrumentation, testing, evaluation, calibration services, and various consultation and information services. Research projects are also performed for other government agencies when the work relates to and supplements the basic program of the Bureau or when the Bureau's unique competence is required. The scope of activities is suggested by the listing of divisions and sections on the inside of the back cover.

Publications

The results of the Bureau's research are published either in the Bureau's own series of publications or in the journals of professional and scientific societies. The Bureau publishes three periodicals available from the Government Printing Office: The Journal of Research, published in four separate sections, presents complete scientific and technical papers; the Technical News Bulletin presents summary and preliminary reports on work in progress; and the Central Radio Propagation Laboratory Ionospheric Predictions provides data for determining the best frequencies to use for radio communications throughout the world. There are also five series of nonperiodical publications: Monographs, Applied Mathematics Series, Handbooks, Miscellaneous Publications, and Technical Notes.

A complete listing of the Bureau's publications can be found in National Bureau of Standards Circular 460, Publications of the National Bureau of Standards, 1901 to June 1947 (\$1.25), and the Supplement to National Bureau of Standards Circular 460, July 1947 to June 1957 (\$1.50), and Miscellaneous Publication 240, July 1957 to June 1960 (includes Titles of Papers Published in Outside Journals 1950 to 1959) (\$2.25); available from the Superintendent of Documents, Government Printing Office, Washington 25, D.C.

NATIONAL BUREAU OF STANDARDS REPORT

NBS PROJECT

1205-12-12450

NBS REPORT

8022

June 27, 1963

MARKOV CHAIN ANALYSIS OF A SORTING MACHINE

by

Joel Levy

Operations Research Section

Applied Mathematics Division

For

Data Processing Systems Division

Post Office Mechanization Project

IMPORTANT NOTICE

NATIONAL BUREAU OF STANDARDS
for use within the Government. It
and review. For this reason, the
whole or in part, is not authorized
Bureau of Standards, Washington
the Report has been specifically p

Approved for public release by the
director of the National Institute of
Standards and Technology (NIST)
on October 9, 2015

Accounting documents intended
subjected to additional evaluation
listing of this Report, either in
Office of the Director, National
the Government agency for which
copies for its own use.



U. S. DEPARTMENT OF COMMERCE
NATIONAL BUREAU OF STANDARDS

ABSTRACT

Markov Chain Analysis of a Sorting Machine

A method is developed for describing an automatic sorter which is being used simultaneously for sorting operations by several clerks. Some information concerning the behaviour of differently designed machines under varying conditions can be obtained from this description.

CONTENTS

1. BACKGROUND.....	1
2. LOCAL PICTURE OF MACHINE.....	1
3. SEQUENCE OF STEPS IN EVENT.....	1
4. LABELLING OF STATES.....	2
5. LOCAL TRANSFORMATIONS.....	3
6. OPERATION TRANSITION MATRIX ($b=0$).....	3
7. MARKOV MATRIX ($b=0$).....	4
8. OPERATION TRANSITION MATRIX ($b > 0$).....	5
9. MARKOV MATRIX ($b > 0$).....	6
10. FUNCTIONS OF b and p_j ($j=0,1,2,3$).....	6
11. DEFICIENCY MEASURES OF MACHINE.....	7

1. BACKGROUND

For the motivation of the model to be discussed and its general formulation reference is made to "Analysis of Overflow Rate in a Sorting System" by B.K. Bender and A.J. Goldman (National Bureau of Standards Report # 7513, May 1, 1962). In particular see sections one thru four of that report. We translate the Bender-Goldman report into the notation of Markov matrices and its terminology. This is done so that the methods of Markov Chains can be applied.

2. LOCAL PICTURE OF MACHINE

The discussion will be confined to events at the intersection of a given operator belt and a given destination belt when the feed in on the destination belt and operator belt are sequentially independent, i.e. whether or not a package arrives at a given moment is independent of whether or not one arrived at previous moments. (We use "destination belt" for "cross belt" in the report cited above). If an operator-destination intersection at one of the intersection points from which the destination belt is coming has a buffer with positive capacity, the transitions of the local state of the machine are not governed by a Markov process. A more complete description of the machine than is given here would be necessary in order that the change of state may be probabilistically determined by the present state of the machine. A treatment of the more general case is in preparation.

3. SEQUENCE OF STEPS IN EVENT

The following sequence of steps in the machine operation is postulated:

- a) the operator belt acts (it either puts out a package or it

does not put a package off at the intersection). The package, if one is put out, enters the destination tray, if it is empty, or enters the buffer, if the buffer is not filled to capacity and the destination tray is occupied, or overflows (this is recorded in step d),

b) new destination tray (empty or occupied) arrives,

c) buffer discharges, i.e. if buffer is occupied and tray arrives empty then one package moves from the buffer to the destination tray; if one of these conditions does not hold then the number of packages in the buffer is unchanged,

d) new state of the system (defined in the following section) is recorded and back to step a.

4. LABELLING OF STATES

The possible states and the labelling system that will be used to identify them are the following for $b > 0$:

$S_1 \equiv$ destination belt empty (this implies buffer empty)

$S_2 \equiv$ destination belt occupied, buffer empty

$S_3 \equiv$ buffer has one package

* * * * *

$S_{b+2} \equiv$ buffer has b packages (filled to capacity)

$S_{b+3} \equiv$ buffer has $b-1$ packages and overflow just occurred

$S_{b+4} \equiv$ buffer has b packages and overflow just occurred

For $b=0$, S_1 and S_2 are as above and the remaining states are:

$S_3 \equiv$ destination belt empty and overflow has just occurred

$S_4 \equiv$ destination belt occupied and overflow has just occurred.

5. LOCAL TRANSFORMATIONS

Four transformations on the local state of the machine are assumed. We denote them as follows:

$$T_0 = (0,0)$$

$$T_1 = (0,1)$$

$$T_2 = (1,0)$$

$$T_3 = (1,1)$$

In the ordered pairs above a zero on the right indicates that the operator belt did not put out a package, and a one on the right indicates the operator belt did put out a package. A zero on the left indicates the absence of a package on the newly arrived destination tray. A one on the left indicates the presence of a package on the newly arrived destination tray.

The mnemonic justification of the above notation is that the symbols indicating given operations are written from right to left in the order of application specified in section 3. Then the ordered pairs indicating the composition of the two operations are labelled with the integer whose binary representation they are.

6. OPERATION TRANSITION MATRIX (b=0)

The effect of the above transformations on the machine states is conveniently described by a matrix, i.e. a rectangular array of the symbols labelling the states of the machine; no algebraic structure is intended.

The matrix for $b=0$ is as follows:

	S_1	S_2	S_3	S_4
T_0	S_1	S_1	S_1	S_1
T_1	S_1	S_3	S_1	S_3
T_2	S_2	S_2	S_2	S_2
T_3	S_2	S_4	S_2	S_4

The matrix is to be read as follows: Given the machine is in state S_i and transformation operation T_j is applied, the new state of the machine is the entry in column i , row j .

7. MARKOV MATRIX ($b=0$)

Assuming that transition operator T_j will be used with probability p_j , the Markov matrix appropriate to the process governing the machine states can be derived from the operation transition matrix. The entries of each row of the Markov matrix are gotten from the corresponding column of the operation transition matrix as follows:

- 1) operation transition matrix column i , row j , entry S_k , yields
- 2) Markov transition matrix row i , column k , entry p_j .

If a given column in the operation transition matrix has more than one entry S_k , the different p_j 's are summed to form the appropriate Markov matrix entry. In other words, the probability of transition from S_i to S_k (i.e. the entry in row i and column k of the Markov transition matrix) is the sum of those p_j 's for which T_j operating on S_i yields S_k (i.e. for which S_k appears in row j and column i of the operation transition matrix), and is zero if there are no such p_j 's.

The Markov transition matrix for $b=0$ is:

	S_1	S_2	S_3	S_4
S_1	p_0+p_1	p_2+p_3	0	0
S_2	p_0	p_2	p_1	p_3
S_3	p_0+p_1	p_2+p_3	0	0
S_4	p_0	p_2	p_1	p_3

8. OPERATION TRANSITION MATRIX ($b > 0$)

For $b > 0$, the operation transition matrix has 4 rows and $b+4$ columns:

- 1) The first column is: $[S_1, S_1, S_2, S_2]^T$,
- 2) The j th column, for $j=2, \dots, b+1$, consists of:

$$[S_{j-1}, S_j, S_j, S_{j+1}]^T.$$

- 3) Column $(b+3)$ is the same as column $(b+1)$.
- 4) Columns $(b+2)$ and $(b+4)$ are:

$$[S_{b+1}, S_{b+3}, S_{b+2}, S_{b+4}]^T.$$

	S_1	S_2		S_{b+1}	S_{b+2}	S_{b+3}	S_{b+4}
T_0	S_1	S_1	*	S_b	S_{b+1}	S_b	S_{b+1}
T_1	S_1	S_2	*	S_{b+1}	S_{b+3}	S_{b+1}	S_{b+3}
T_2	S_2	S_2	*	S_{b+1}	S_{b+2}	S_{b+1}	S_{b+2}
T_3	S_2	S_3	*	S_{b+2}	S_{b+4}	S_{b+2}	S_{b+4}

It is readily verified from the definitions of the states and of the operation transition matrix that when the number of local states in the machine is $b+4$ the column headed S_{b+3} (S_{b+4}) is identical with the column headed S_{b+1} (S_{b+2}).

9. MARKOV MATRIX ($b > 0$)

The Markov matrix is constructed from the operation transition matrix as explained above in section 7, where the process was carried out for the case $b=0$. For $b > 3$ the corner entries will be as follows:

	S_1	S_2	S_b	S_{b+1}	S_{b+2}	S_{b+3}	S_{b+4}
S_1	$p_0 + p_1$	$p_2 + p_3$	0	0	0	0	0
S_2	p_0	$p_1 + p_2$	0	0	0	0	0
S_3	0	p_0	0	0	0	0	0
*	*	*	*	*	*	*	*
*	*	*	*	*	*	*	*
S_{b+1}	0	0	p_0	$p_1 + p_2$	p_3	0	0
S_{b+2}	0	0	0	p_0	p_2	p_1	p_3
S_{b+3}	0	0	p_0	$p_1 + p_2$	p_3	0	0
S_{b+4}	0	0	0	p_0	p_2	p_1	p_3

10. FUNCTIONS OF b and p_j ($j=0,1,2,3$)

For a range of values of b , and p_j ($j=0,1,2,3$) the following quantities are of interest:

- 1) the expected, i.e. mean, proportion of time that the machine will be in each of the states,
- 2) the expected proportion of time there will be an overflow,
- 3) the expected proportion of time the destination tray will leave the operator position intersection empty,

4) from the frequency function of (1):

- a) distribution function of the number of empty buffer positions
(distribution function of the number of occupied buffer positions)
- b) frequency function of the number of empty buffer positions
(frequency function of the number of occupied buffer positions)
- c) expected number of empty buffer positions.

11. DEFICIENCY MEASURES OF MACHINE

Of the quantities above, 2) the expected proportion of time there will be an overflow, 3) the expected proportion of time the destination tray will leave the operator position empty, and 4c) the expected number of empty buffer positions for the steady-state probability of the given Markov chain, are each a measure of deficiency of the machine for the given parameter values.



THE NATIONAL BUREAU OF STANDARDS

The scope of activities of the National Bureau of Standards at its major laboratories in Washington, D.C., and Boulder, Colorado, is suggested in the following listing of the divisions and sections engaged in technical work. In general, each section carries out specialized research, development, and engineering in the field indicated by its title. A brief description of the activities, and of the resultant publications, appears on the inside of the front cover.

WASHINGTON, D. C.

Electricity. Resistance and Reactance. Electrochemistry. Electrical Instruments. Magnetic Measurements. Dielectrics. High Voltage. Absolute Electrical Measurements.

Metrology. Photometry and Colorimetry. Refractometry. Photographic Research. Length. Engineering Metrology. Mass and Volume.

Heat. Temperature Physics. Heat Measurements. Cryogenic Physics. Equation of State. Statistical Physics.

Radiation Physics. X-ray. Radioactivity. Radiation Theory. High Energy Radiation. Radiological Equipment. Nucleonic Instrumentation. Neutron Physics.

Analytical and Inorganic Chemistry. Pure Substances. Spectrochemistry. Solution Chemistry. Standard Reference Materials. Applied Analytical Research. Crystal Chemistry.

Mechanics. Sound. Pressure and Vacuum. Fluid Mechanics. Engineering Mechanics. Rheology. Combustion Controls.

Polymers. Macromolecules: Synthesis and Structure. Polymer Chemistry. Polymer Physics. Polymer Characterization. Polymer Evaluation and Testing. Applied Polymer Standards and Research. Dental Research.

Metallurgy. Engineering Metallurgy. Metal Reactions. Metal Physics. Electrolysis and Metal Deposition.

Inorganic Solids. Engineering Ceramics. Glass. Solid State Chemistry. Crystal Growth. Physical Properties. Crystallography.

Building Research. Structural Engineering. Fire Research. Mechanical Systems. Organic Building Materials. Codes and Safety Standards. Heat Transfer. Inorganic Building Materials. Metallic Building Materials.

Applied Mathematics. Numerical Analysis. Computation. Statistical Engineering. Mathematical Physics. Operations Research.

Data Processing Systems. Components and Techniques. Computer Technology. Measurements Automation. Engineering Applications. Systems Analysis.

Atomic Physics. Spectroscopy. Infrared Spectroscopy. Far Ultraviolet Physics. Solid State Physics. Electron Physics. Atomic Physics. Plasma Spectroscopy.

Instrumentation. Engineering Electronics. Electron Devices. Electronic Instrumentation. Mechanical Instruments. Basic Instrumentation.

Physical Chemistry. Thermochemistry. Surface Chemistry. Organic Chemistry. Molecular Spectroscopy. Elementary Processes. Mass Spectrometry. Photochemistry and Radiation Chemistry.

Office of Weights and Measures.

BOULDER, COLO.

CRYOGENIC ENGINEERING LABORATORY

Cryogenic Processes. Cryogenic Properties of Solids. Cryogenic Technical Services. Properties of Cryogenic Fluids.

CENTRAL RADIO PROPAGATION LABORATORY

Ionosphere Research and Propagation. Low Frequency and Very Low Frequency Research. Ionosphere Research. Prediction Services. Sun-Earth Relationships. Field Engineering. Radio Warning Services. Vertical Soundings Research.

Troposphere and Space Telecommunications. Data Reduction Instrumentation. Radio Noise. Tropospheric Measurements. Tropospheric Analysis. Spectrum Utilization Research. Radio-Meteorology. Lower Atmosphere Physics.

Radio Systems. Applied Electromagnetic Theory. High Frequency and Very High Frequency Research. Frequency Utilization. Modulation Research. Antenna Research. Radiodetermination.

Upper Atmosphere and Space Physics. Upper Atmosphere and Plasma Physics. High Latitude Ionosphere Physics. Ionosphere and Exosphere Scatter. Airglow and Aurora. Ionospheric Radio Astronomy.

RADIO STANDARDS LABORATORY

Radio Standards Physics. Frequency and Time Disseminations. Radio and Microwave Materials. Atomic Frequency and Time-Interval Standards. Radio Plasma. Microwave Physics.

Radio Standards Engineering. High Frequency Electrical Standards. High Frequency Calibration Services. High Frequency Impedance Standards. Microwave Calibration Services. Microwave Circuit Standards. Low Frequency Calibration Services.

Joint Institute for Laboratory Astrophysics-NBS Group (Univ. of Colo.).

